

Product data sheet

NOT 320 AP *



Emergency exit system emergency push button for mains voltage shut-off in the case of an emergency or during maintenance work, surface-mounted installation

AREAS OF APPLICATION

- Mains voltage shut-off in the case of an emergency and during maintenance work
- Indirect release of GEZE emergency exit system door control units
- Opening of automatic doors in case of an emergency



PRODUCT FEATURES

- LED lighting for better visibility, even in the dark
- Re-usable cover that protects against dust and dirt
- Contact system consists of one normally closed contact and one normally opened contact
- Plastic housing offers the possibility of surface-mounted installation
- Flat impact cover enables fast and safe activation of the illuminated emergency push button in panic situations

TECHNICAL DATA

Productname	NOT 320 AP *
Supply voltage	24 V DC
Current consumption	30 mA
Type of installation	Surface-mounted
Service temperature	-10 - 50 °C

VARIANTS / ORDER INFO

Designation	Description	Ident-No.	Colour	Operating voltage	Type of installation
NOT 320 AP emergency push button, Jung AS 500 *	with surface mounted cap Jung AS 500 and single frame / Impact cover made of transparent plastic / Impact cover dimensions 55 x 55 mm / Operating voltage: 24 V DC / Current consumption: 30 mA / 1 normally closed contact / 1 normally open contact / Contact current capacity: 1A, 30 V	137967	alpine white	24 V DC	Surface-mounted

* The products designated above may vary in form, type, characteristics, function, or availability depending on the country. Please get in touch with your GEZE contact person if you have any questions.